Bourns® POWrFuse™ High-Power Fuses Product Guide

POWrFus	POWrFuse™ INDUSTRIAL POWER FUSES								
Model Series	Mounting Type	Dimensions (mm)	Rated Current	Rated Voltage	Interrupting Rating	Agency Recognition			
<u>PF-J</u>	PCB/T3	10.4 dia. x 38.5	30-70 A	500 VAC 125 VDC	2000 A @ 500 VAC 2000 A @ 250 VAC 1000 A @ 125 VDC	c FN [®] us			
<u>PF-G</u>		14.6 dia. x 38.5	63 A	600 VAC 125 VDC	1500 A @ 600 VAC 2000 A @ 250 VAC 500 A @ 125 VDC	c AU [®] us			
	PCB/T3		90 A	500 VAC	1500 A @ 500 VAC				
<u> PF-H (ind)</u>	Ferrule/C1	10 dia. x 38	6-12 A	600 VAC 600 VDC	100 kA @ 600 VAC 100 kA @ 600 VDC				

POWrFuse[™] PHOTOVOLTAIC POWER FUSES

Model Series	Mounting Type		Dimensions (mm)	Rated Current	Rated Voltage	Interrupting Rating	Agency Recognition
<u> PF-H (gPV)</u>	Ferrule/C1	PCB/T1	10 dia. x 38	15-30 A	600 VAC 600 VDC	150 kA @ 600 VAC 50 kA @ 600 VDC 10 kA @ 600 VDC	
<u>PF-E</u>	Ferrule/C1	PCB/T1	10 dia. x 38	15-30 A	1000 VDC	20 kA @1000 VDC	

POWrFuse™ SEMICONDUCTOR POWER FUSES

Mode	el Series	Mounting Type	Dimensions (mm)	Rated Current	Rated Voltage	Interrupting Rating	Agency Recognition
<u>Pf</u>	<u>F-M</u>	Bolt/B1	17.2 dia. x 42	50-180 A	240 VAC 150 VDC	160 kA @ 240 VAC 50 kA @ 150 VDC	c FN ° us
P	PF-F Bolt/B1		24.1 dia. x 91.6 35.2 dia. x 95	50-400 A	800 VAC 800 VDC	100 kA @ 800 VAC 50 kA @ 800 VDC	c FN ° us

POWrFuse[™] EV POWER FUSES^{*} *GRADE GRADE*

Model Series	Mounting Type		Dimensions (mm)	Rated Current	Rated Voltage	Interrupting Rating	Qualifications
<u>PF-K</u>	Bolt/B1	PCB/T1	10 dia. x 38	30-50 A	275 VAC 500 VDC	10 kA @ 275 VAC 20 kA @ 500 VDC 10 kA @ 450 VDC	ISO 8820

POWrFuse[™] TELECOM POWER FUSES

Model Serie	S Mounti	ng Type	Dimensions (mm)	Rated Current	Rated Voltage	Interrupting Rating	Agency Recognition
<u>PF-N</u>	PCB/T2	PCB/T5	14.6 dia. x 22.3	40-80 A	170 VDC	100 kA @ 170 VDC	c FN [®] us

* Meets ISO8820-8 standard